



## MFP Summary of Devices and Agents

MFP Summary of Devices and Agents		
1	<b>Agent PC/Server</b>	<ul style="list-style-type: none"> <li>Select the link to remove associated MFPs or the agent.</li> <li>If removing the agent, uninstall it from the PC or server using the normal Windows uninstall procedure to complete removal and avoid reconnection.</li> <li>Select <b>Find MFPs</b> to access <b>SNMP Configuration</b> and initiate MFP discovery.</li> </ul>
2	<b>Agent ID/ IP Address</b>	<ul style="list-style-type: none"> <li>Select the <b>Log</b> link to view the system log for error or status messages.</li> <li>Each system log entry has an error code (e.g. C102) at the end of the message, which provides more detailed information on the log entry. Contact your Sharp service provider for details.</li> <li>A grey agent ID indicates the agent has not been used for 14 days or longer.</li> <li>A red triangle next to the agent ID indicates an agent error (e.g. agent is disconnected) that needs to be addressed.</li> <li>Select the <b>envelope icon</b>  to acquire the agent log files from the agent PC or server and email a link to the files to up to five email addresses. The log file will upload to the Synappx cloud and the link will be added to the email after selecting <b>Send</b>. The log link will remain active for seven days.</li> </ul> <div data-bbox="912 808 1497 1290" style="border: 1px solid black; padding: 5px; margin-top: 10px;"> <p>Email Agent Log <span style="float: right;">Agent PC: PC123</span></p> <p style="text-align: right;"><span style="color: orange;">* Mandatory</span></p> <p><b>To</b> *: <span style="float: right;">5 addresses max</span> admin@domain.com</p> <hr/> <p><b>Subject:</b> Synappx Go Agent Log for desktop-1k40eeg</p> <hr/> <p><b>Message:</b> <span style="float: right;">The Link to the agent Log will be added automatically</span> Click Link to open agent log</p> <hr/> <p style="color: orange; font-size: small;">Note: The Log is available for next 7 days.</p> <p style="text-align: right;"><span style="background-color: #00a0e3; color: white; padding: 2px 5px; border-radius: 5px;">Send</span> <span style="background-color: #ccc; padding: 2px 5px; border-radius: 5px;">Cancel</span></p> </div>
3	<b>Version</b>	Select the agent version number to go to the <b>Agent Update</b> page.
4	<b>Updates</b>	<ul style="list-style-type: none"> <li>An orange dot indicates a recent agent version requiring an update.</li> <li>A red dot indicates an outdated agent version requiring an update.</li> </ul>
5	<b>Device</b>	<ul style="list-style-type: none"> <li>Select the device view details.</li> <li>Select <b>Show All Devices</b> to view all associated and unassigned MFPs.</li> </ul>
6	<b>Workspace</b>	<ul style="list-style-type: none"> <li>Select a workspace to view associated devices.</li> </ul>

Design and specifications subject to change without notice. All information was correct at time of print. Sharp, Synappx and all related trademarks are trademarks or registered trademarks of Sharp Corporation and/or its affiliated companies. © Sharp Corporation August 2020. Ref: MFP Summary of Devices and Agents.